

MIRACLE SWITCH DL517 by DOWN and LOCKED

Down and Locked's 15 AMP MIRACLE SWITCH AND REGULATOR provides a 15amp current path and low amp cut off switch. Connections are two Female JR connectors are provided as battery inputs and two male JR as outputs to your model. Plug in the on/off switch, adjust the voltage and you are ready to go, 5V factory set.

Installation:

- 1) Connect input power to the female JR connectors
- 2) With a small screw driver adjust the voltage to your models requirements
- 3) Using a volt meter verify the adjusted voltage on the Brown (-) and the Plus (+) wires of the male JR connector out.
- 4) Connect the ON/Off switch and mount in your model, it can be extended to the length you need with a JR extension

Specifications:

Input Voltage Range: to 16 Volts
Output Voltage Range: ~4.7 - ~ Aprox Bat Volts
Output Current: 15.0 Amps (continuous and peak)
Temperature Range: -40 to 85 deg C (-40 to 185deg F)
Weight: 20 grams

Warranty and Support:

180 day warranty materials and workmanship. Perform range tests prior to flight.

www.DOWNANDLOCKED.COM